

Mhouse DS1

Digital switch with programmable code via radio. Safe and clever, exclusive design



13-key digital switch with programmable code, via radio.



Radio controlled digital keypad:
easy installation of a wireless device
with the safety of the rolling code system.
Compatible with the Mhouse receivers
with rolling code technology.
It generates 18 billion billion combinations,
with self-learning functions

Handy: no wiring necessary,
100m outdoors (35m indoor range)

Strong: vandal-proof die-cast
aluminum casing, IP44

Complete: 3 transmission channels
to control as many automations

Light-up-when-necessary button

Technical specifications DS1

Frequency (MHz)	433.92 ± 100KH
Radio coding	rolling code 64bit
Range (m)	100; 35 if inside buildings
Power supply	6Vdc with 2 CR2430 type lithium batteries
Battery life (estimated)	2 years with 10 transmissions per day
No. of figure combination	from 0 to 10
Protection rating (IP)	44
Dimensions (mm)	65x95x33
Weight (g)	260

Safe: 9.999.999.999 possible combinations
by choosing a number from 0 up to 10 figures

Clever: very easy code-changing.
The same system used for mobile phone
with PUK code in case you forget the one
you programmed

Cheap: extra low consumption,
transmission is activated when any key
is pressed and it switches itself off
automatically

mhouse

Mhouse srl
Via Pezza Alta 13
31046 Oderzo TV Italia
Tel. +39 0422 202 109
Fax +39 0422 852 582
info@mhouse.biz
www.mhouse.com